

12V power supply cable for the JA-107K control panel

The JA-107K control panel makes it possible to utilize an external power supply which is in conformity with EN 50131-6. The power supply must be within the range of 10 to 15 V (DC) and intended for use in remote system installations and/or objects without a constant 230 V (AC) power supply.

In order to connect the external power supply, we recommend the use of a VOD-JA-107K cable. It is comprised of a conductor, a fuse box containing a fuse (F 6,3 A) and a connector.

Installation procedure:

- Disconnect the cable connected to the control panel's power supply unit (the internal power supply, including it's backup accumulator will no longer be in use with the utilization of this configuration).
- Connect the power supply cable to the external power supply, the power supply must be off.
- Insert the cable's connector into the control panel unit's circuit board slot.
- Turn on the external power supply.

Notes:

- If this configuration is utilized, the control panel unit no longer monitors the current status of the power supply unit, not it's battery backup.
- System backup is solely dependent on the reliability of the external power supply.
- Using an alternate external power supply may result in damages for which the manufacturer bears no responsibility.



Note: Disposing of this product correctly will help save valuable resources and prevent any potential negative effects on human health and the environment, which could otherwise arise from inappropriate waste handling. Please return the product to the dealer or contact your local authority for further details of your nearest designated collection point.

JABLOTRON
CREATING ALARMS

JABLOTRON ALARMS a.s.
Pod Skalkou 4567/33
46601 Jablonec nad Nisou
Czech Republic
Tel.: +420 483 559 911
Fax: +420 483 559 993
Internet: www.jablotron.com